

LIGHTING FIXTURE SCHEDULE										
MARK	VOLT	WATT	LAMP		MOUNTING			MANUFACTURER	CATALOG NO.	REMARKS
			CCT	TYPE	BRKT	PEND	REC			
A	UNV	49	4000K	LED			X	H.E. WILLIAMS	LT-24-L64/840-AF-GS-DIM-UNV	6400 LUMEN 2X4 LED TROFFER
A2	UNV	49	4000K	LED			X	H.E. WILLIAMS	LT-22-L40/840-AF-DIM-UNV	4000 LUMEN 2X2 LED TROFFER
B	UNV	31	4000K	LED			X	LSI LIGHTING	XSP5-S-LED-SS-NW-120-GNT-DFL-CMT SOFFIT	5000 LUMEN LED SOFFIT LIGHT
B1	UNV	36	4000K	LED			X	H.E. WILLIAMS	6DR-L40/840-OPTIONS-DIM-UNV	6IN ROUND DOWNLIGHT
D	UNV	33	4000K	LED			X	H.E. WILLIAMS	755-4-L50/840-DIM-UNV	5000 LUMEN 1X4 STRIP
E	UNV	5	N/A	LED			X	MULE LIGHTING	MERU-LED-ACEM-WH	EXTERIOR EMERGENCY LIGHT
F	UNV	57	4000K	LED		X		SPI LIGHTING	AIP11989-L57N-UNV-4000K-DF-AC	4FT 2.5IN DECORATIVE PENDANT SUSPEND 1FT 7IN FROM CEILING TILE
G	UNV	20	4000K	LED		X		H.E. WILLIAMS	755-4-L30/840-DIM-UNV	3000 LUMEN STRIP TROPHY CASE LIGHT
H	UNV	1	N/A	LED			X	MULE LIGHTING	R-ASRLED-1-WP-W	REMOTE HEAD EMERGENCY EXTERIOR LIGHT
⊗	UNV	5	N/A	LED			X	MULE LIGHTING	PVT-U-B-R-S/R-BA-SD	EXIT SIGN
⊗R	UNV	5	N/A	LED			X	MULE LIGHTING	PVT-U-B-R-S/R-BA-REM	EXIT SIGN WITH REMOTE HEAD CAPABILITIES
⊗L	UNV	5	N/A	LED			X	MULE LIGHTING	70-T-O-B	PHOTOLUMINUS EXIT SIGN

NOTES:
 NOTE : HOLD ALL INSULATION OFF RECESSED FIXTURES AND A MINIMUM OF 3" TO THE SIDE.
 NOTE : EXIT LIGHTS AND EMERGENCY LIGHTS REQUIRES UNSWITCHED HOT WIRE PER MANUFACTURER RECOMMENDATION.
 NOTE : ELECTRICAL CONTRACTOR TO PROVIDE AND INSTALL DRIVER AND LEDS THAT WILL PROVIDE THE OWNER WITH A FIVE YEAR WARRANTY.
 NOTE : EM DENOTES EMERGENCY BATTERY PACK GOOD FOR 1.5 HOURS.

GENERAL LIGHTING NOTES

1. NEW SWITCHES AND OCCUPANCY SENSORS ARE TO BE LUTRON VIVE PROVIDE AND PROGRAM TO HUB. CONNECT HUB TO NEAREST EXISTING RECEPTACLE CIRCUIT.

LIGHTING KEYED NOTES

- ① REPLACE DAMGED EXTERIOR DOWNLIGHT. COORDINATE WITH OWNER FOR EXACT LOCATION. CONNECT TO EXISTING EXTERIOR LIGHTING CIRCUITRY. EXTEND AS REQUIRED.
- ② REPLACE LIGHTS LOCATED AT UPPER SOFFIT ABOVE AIRLOCK 100A. FIELD VERIFY EXACT LOCATION. CONNECT TO EXISTING EXTERIOR LIGHTING CIRCUITRY. EXTEND AS REQUIRED.
- ③ REPLACE DAMAGED EXTERIOR DOWNLIGHT. PROVIDE NEW CIRCUITRY BACK TO EXISTING EXTERIOR LIGHTING CIRCUIT THAT IS LOCATED OUTSIDE OF THE REMODELED AREA.
- ④ CENTER FIXTURE WITHIN OVERALL CEILING GRID SHARE. EXISTING FIXTURES ARE NOT CENTERED. ADJUST POWER SUPPLY TO NEW LOCATION.
- ⑤ PROTECT EXISTING PARABOLIC GRILLE TO REMAIN.
- ⑥ CONDUIT LOCATED IN EXISTING ROOF SLAB. FIELD VERIFY EXACT LOCATIONS.

