

**SECTION 26 09 23**  
**LIGHTING CONTROLS**

**PART 1 - GENERAL**

**1.1 DESCRIPTION**

This section specifies the furnishing, installation, and connection of the lighting controls.

**1.2 RELATED WORK**

- A. Section 23 09 23, DIRECT-DIGITAL CONTROL SYSTEM FOR HVAC: Interface of lighting controls with HVAC control systems.
- B. Section 26 05 11, REQUIREMENTS FOR ELECTRICAL INSTALLATIONS: General requirements that are common to more than one section of Division 26.
- C. Section 26 05 19, LOW-VOLTAGE ELECTRICAL POWER CONDUCTORS AND CABLES: Cables and wiring.
- D. Section 26 05 26, GROUNDING AND BONDING FOR ELECTRICAL SYSTEMS: Requirements for personnel safety and to provide a low impedance path to ground for possible ground fault currents.
- E. Section 26 24 16, PANELBOARDS: Panelboard enclosure and interior bussing used for lighting control panels.
- F. Section 26 27 26, WIRING DEVICES: Wiring devices used for control of the lighting systems.
- G. Section 26 51 00, INTERIOR LIGHTING: Luminaire ballast and drivers used in control of lighting systems.

**1.3 QUALITY ASSURANCE**

- A. Quality Assurance shall be in accordance with Paragraph, QUALIFICATIONS (PRODUCTS AND SERVICES) in Section 26 05 11, REQUIREMENTS FOR ELECTRICAL INSTALLATIONS.

**1.4 SUBMITTALS**

- A. Submit in accordance with Paragraph, SUBMITTALS in Section 26 05 11, REQUIREMENTS FOR ELECTRICAL INSTALLATIONS, and the following requirements:
  - 1. Shop Drawings:
    - a. Submit the following information for each type of lighting controls.
    - b. Material and construction details.
    - c. Physical dimensions and description.
    - d. Wiring schematic and connection diagram.
    - e. Installation details.
  - 2. Manuals:

- a. Submit, simultaneously with the shop drawings, complete maintenance and operating manuals, including technical data sheets, wiring diagrams, and information for ordering replacement parts.
- b. If changes have been made to the maintenance and operating manuals originally submitted, submit updated maintenance and operating manuals two weeks prior to the final inspection.
- 3. Certifications: Two weeks prior to final inspection, submit the following.
  - a. Certification by the Contractor that the lighting control systems have been properly installed and tested.

#### **1.5 APPLICABLE PUBLICATIONS**

- A. Publications listed below (including amendments, addenda, revisions, supplements, and errata) form a part of this specification to the extent referenced. Publications are referenced in the text by designation only.
- B. National Electrical Manufacturer's Association (NEMA):
  - C136.10-10.....American National Standard for Roadway and Area Lighting Equipment—Locking-Type Photocontrol Devices and Mating Receptacles—Physical and Electrical Interchangeability and Testing
  - ICS-1-15.....Standard for Industrial Control and Systems General Requirements
  - ICS-2-05.....Standard for Industrial Control and Systems: Controllers, Contractors, and Overload Relays Rated Not More than 2000 Volts AC or 750 Volts DC: Part 8 - Disconnect Devices for Use in Industrial Control Equipment
  - ICS-6-16.....Standard for Industrial Controls and Systems Enclosures
- C. National Fire Protection Association (NFPA):
  - 70-17.....National Electrical Code (NEC)
- D. Underwriters Laboratories, Inc. (UL):
  - 20-10.....Standard for General-Use Snap Switches
  - 98-16.....Enclosed and Dead-Front Switches
  - 773-16.....Standard for Plug-In Locking Type Photocontrols for Use with Area Lighting

773A-16.....Nonindustrial Photoelectric Switches for  
Lighting Control

916-15.....Standard for Energy Management Equipment  
Systems

917-06.....Clock Operated Switches

924-16.....Emergency Lighting and Power Equipment (for use  
when controlling emergency circuits).

## **PART 2 - PRODUCTS**

### **2.1 ELECTRONIC TIME SWITCHES: - NOT USED**

### **2.2 ELECTROMECHANICAL-DIAL TIME SWITCHES: - NOT USED**

### **2.3 OUTDOOR PHOTOELECTRIC SWITCHES: - NOT USED**

### **2.4 TIMER SWITCHES: - NOT USED**

### **2.5 CEILING-MOUNTED PHOTOELECTRIC SWITCHES: - NOT USED**

### **2.6 SKYLIGHT PHOTOELECTRIC SENSORS: - NOT USED**

### **2.7 INDOOR OCCUPANCY SENSORS:**

- A. Wall- or ceiling-mounting, solid-state units with a power supply and relay unit, suitable for the environmental conditions in which installed.
  - 1. Operation: Unless otherwise indicated, turn lights on when covered area is occupied and off when unoccupied; with a 1 to 15 minute adjustable time delay for turning lights off.
  - 2. Sensor Output: Contacts rated to operate the connected relay. Sensor shall be powered from the relay unit.
  - 3. Relay Unit: Dry contacts rated for 20A ballast load at 120 volt and 277 volt, for 13A tungsten at 120 volt, and for 1 hp at 120 volt.
  - 4. Mounting:
    - a. Sensor: Suitable for mounting in any position on a standard outlet box.
    - b. Time-Delay and Sensitivity Adjustments: Recessed and concealed behind hinged door.
  - 5. Indicator: LED, to show when motion is being detected during testing and normal operation of the sensor.
  - 6. Bypass Switch: Override the on function in case of sensor failure.
  - 7. Manual/automatic selector switch.
  - 8. Automatic Light-Level Sensor: Adjustable from 21.5 to 2152 lx (2 to 200 fc); keep lighting off when selected lighting level is present.

9. Faceplate for Wall-Switch Replacement Type: Refer to wall plate material and color requirements for toggle switches, as specified in Section 26 27 26, WIRING DEVICES.
- B. Dual-technology Type: Ceiling mounting; combination PIR and ultrasonic detection methods, field-selectable.
  1. Sensitivity Adjustment: Separate for each sensing technology.
  2. Detector Sensitivity: Detect occurrences of 150 mm (6-inch) minimum movement of any portion of a human body that presents a target of not less than 232 sq. cm (36 sq. in), and detect a person of average size and weight moving not less than 305 mm (12 inches) in either a horizontal or a vertical manner at an approximate speed of 305 mm/s (12 inches/s).
- C. Detection Coverage: Shall be sufficient to provide coverage as required by sensor locations shown on drawing.

## **2.8 INDOOR VACANCY SENSOR SWITCH**

- A. Wall mounting, solid-state units with integral sensor and switch.
  1. Operation: Manually turn lights on with switch and sensor detects vacancy to turn lights off.
  2. Switch Rating: 120/277 volt, 1200 watts at 277 volt, 800 watts at 120 volt unit.
  3. Mounting:
    - a. Sensor: Suitable for mounting in a standard switch box.
    - b. Time-Delay and Sensitivity Adjustments: Integral with switch and accessible for reprogramming without removing switch.
  4. Indicator: LED, to show when motion is being detected during testing and normal operation of the sensor.
  5. Switch: Manual operation to turn lights on and override lights off.
  6. Faceplate: Refer to wall plate material and color requirements for toggle switches, as specified in Section 26 27 26, WIRING DEVICES.

**2.9 OUTDOOR MOTION SENSOR (PIR): - NOT USED**

**2.10 LIGHTING CONTROL SYSTEM - RELAY PANEL TYPE (NETWORK): - NOT USED**

**2.11 LIGHTING CONTROL SYSTEM - RELAY PANEL TYPE (STAND ALONE): - NOT USED**

**2.12 LIGHTING CONTROL SYSTEM - DISTRIBUTIVE RELAY TYPE: - NOT USED**

**2.13 LIGHTING CONTROL SYSTEM - CIRCUIT BREAKER PANEL TYPE: - NOT USED**

**2.14 LIGHTING CONTROL SYSTEM - DIGITAL ADDRESSABLE LIGHTING INTERFACE (DALI):  
- NOT USED**

### **PART 3 - EXECUTION**

#### **3.1 INSTALLATION**

- A. Installation shall be in accordance with the NEC, manufacturer's instructions, as shown on the drawings, and as specified.
- B. Aiming for wall-mounted and ceiling-mounted motion sensor switches shall be per manufacturer's recommendations.
- C. Set occupancy sensor "on" duration to 15 minutes.
- D. Locate photoelectric sensors as indicated and in accordance with the manufacturer's recommendations. Adjust sensor for the available light level at the typical work plane for that area.

#### **3.2 ACCEPTANCE CHECKS AND TESTS**

- A. Perform in accordance with the manufacturer's recommendations.
- B. Upon completion of installation, conduct an operating test to show that equipment operates in accordance with requirements of this section.
- C. Test for full range of dimming controls capability. Observe for visually detectable flicker over full dimming range.
- D. Test occupancy sensors for proper operation. Observe for light control over entire area being covered.

#### **3.3 FOLLOW-UP VERIFICATION**

Upon completion of acceptance checks and tests, the Contractor shall show by demonstration in service that the lighting control devices are in good operating condition and properly performing the intended function in the presence of COR.

#### **3.4 INSTRUCTION**

- A. Furnish the services of a factory-trained technician for one 8-hour training period for instructing personnel in the maintenance and operation of the lighting control system on the dates requested by the COR.
- B. Contractor shall submit written instructions on training and maintenance as reviewed in training session.

- - - E N D - - -

This Page Intentionally Left Blank