

RECEPTACLES (MOUNTED 18" AFF UNLESS INDICATED OTHERWISE)

DUPLEX RECEPTACLE OUTLET (20A, 125V, 2 POLE, 3 WIRE, GROUNDING TYPE, NEMA 5-20R)

DUPLEX RECEPTACLE OUTLET (20A, 125V, 2 POLE, 3 WIRE, GROUNDING TYPE, NEMA 5-20R)
MOUNT 4" ABOVE COUNTER TOP, SINK, OR BACKSPLASH (IF PRESENT)

SINGLE RECEPTACLE OUTLET (20A, 125V, 2 POLE, 3 WIRE, GROUNDING TYPE, NEMA 5-20R)

FLOOR RECEPTACLE OUTLET (20A, 125V, 2 POLE, 3 WIRE, GROUNDING TYPE, NEMA 5-20R)

SINGLE RECEPTACLE OUTLET (50A, 250V, 3 POLE, 3 WIRE, NEMA 10-50R)

SINGLE RECEPTACLE OUTLET (20A, 250V, 2 POLE, 3 WIRE, GROUNDING TYPE, NEMA 6-20R)

SINGLE RECEPTACLE OUTLET (30A, 250V, 2 POLE, 3 WIRE, GROUNDING TYPE, NEMA 6-30R)

SINGLE RECEPTACLE OUTLET (30A, 250V, 3 POLE, 4 WIRE, TWIST-LOCK, GROUNDING TYPE, NEMA L15-30R)

SINGLE SPECIAL-PURPOSE RECEPTACLE OUTLET; NUMBER CORRESPONDS TO THE SPECIAL-PURPOSE RECEPTACLE SCHEDULE

SINGLE RECEPTACLE FOR ELECTRIC RANGE (50A, 125/250V, 3 POLE, 4 WIRE, GROUNDING TYPE, NEMA 14-50R)

DUPLEX RECEPTACLE MOUNTED IN CEILING (20A, 125V, 2 POLE, 3 WIRE, GROUNDING TYPE, NEMA 5-20R)

TWO (2) DUPLEX RECEPTACLES MOUNTED IN DOUBLE GANG BACKBOX (20A, 125V, 2 POLE, 3 WIRE, GROUNDING TYPE, NEMA 5-20R)

TWO (2) DUPLEX RECEPTACLES FLOOR MOUNTED IN DOUBLE GANG BACKBOX (20A, 125V, 2 POLE, 3 WIRE, GROUNDING TYPE, NEMA 5-20R)

	LIGHT FIXTURE, CEILING MOUNTED
	LIGHT FIXTURE, CEILING MOUNTED, ON EMERGENCY CIRCUIT
	LIGHT FIXTURE, CEILING MOUNTED, WITH EMERGENCY SELF CONTAINED BATTERY PACK. BATTERY PACK IS TO REMAIN UNSWITCHED.
	LIGHT FIXTURE, WALL MOUNTED
	LIGHT FIXTURE, INDUSTRIAL STRIP, SURFACE OR PENDANT MOUNTED
	LIGHT FIXTURE, INDUSTRIAL STRIP, SURFACE OR PENDANT MOUNTED, ON EMERGENCY CIRCUIT
	LIGHT FIXTURE, INDUSTRIAL STRIP, SURFACE OR PENDANT MOUNTED, WITH EMERGENCY SELF CONTAINED BATTERY PACK. BATTERY PACK IS TO REMAIN UNSWITCHED.
	LIGHT FIXTURE, CEILING MOUNTED
	LIGHT FIXTURE, CEILING MOUNTED, ON EMERGENCY CIRCUIT
	LIGHT FIXTURE, CEILING MOUNTED, WITH EMERGENCY SELF CONTAINED BATTERY PACK. BATTERY PACK IS TO REMAIN UNSWITCHED.
	LIGHT FIXTURE, WALL MOUNTED
	EMERGENCY BATTERY POWERED LIGHTING UNIT, WITH SELF CONTAINED BATTERY, CHARGER, ETC. (REFER TO FIXTURE SCHEDULE FOR BATTERY TYPE, VOLTAGE, LAMP TYPE, WATTAGE, ETC.) TRIANGLES DEPICT QUANTITY AND AIMING OF LAMP HEADS
	EXIT SIGN, LIGHTED, CEILING MOUNTED. SHADED AREA INDICATES FACE. ARROW DEPICTS DIRECTIONAL ARROW ON SIGN. WHEN REQUIRED BY THE FIXTURE SCHEDULE, AN EMERGENCY SELF-CONTAINED BATTERY PACK IS TO REMAIN UNSWITCHED.
	EXIT SIGN, LIGHTED, WALL MOUNTED AT 7'-6" AFF (TO BOTTOM OF SIGN) UNLESS INDICATED OTHERWISE. ARROW DEPICTS DIRECTIONAL ARROW ON SIGN. WHEN REQUIRED BY THE FIXTURE SCHEDULE, AN EMERGENCY SELF-CONTAINED BATTERY PACK IS TO REMAIN UNSWITCHED.
	FLOOD LIGHT, ARROW INDICATES DIRECTION OF BEAM
	DOCK LIGHT
	PARKING AREA LIGHT FIXTURE, POLE MOUNTED

Diagram illustrating the labeling convention for a fixture:

- UPPER CASE LETTER BESIDE EACH FIXTURE DENOTES FIXTURE TYPE.
- LOWER CASE LETTER BESIDE FIXTURE DENOTES SWITCH CONTROL (WHERE APPLICABLE).

TELEPHONE/COMMUNICATIONS/DATA (OUTLETS SHALL BE MOUNTED 18" AFF UNLESS INDICATED OTHERWISE)	
▶	TELEPHONE OUTLET. OUTLET BOX WITH 1" C STUBBED ABOVE ACCESSIBLE CEILING SPACE AND PULL CORD. SUBSCRIPT: W- WALL MOUNTED AT 54" AFF.
☑	TELEPHONE FLOOR OUTLET. OUTLET BOX WITH 1" C STUBBED ABOVE ACCESSIBLE CEILING SPACE AND PULL CORD.
▷	DATA OUTLET. OUTLET BOX WITH 1" C STUBBED ABOVE ACCESSIBLE CEILING SPACE AND PULL CORD.
☑	DATA FLOOR OUTLET. OUTLET BOX WITH 1" C STUBBED ABOVE ACCESSIBLE CEILING SPACE AND PULL CORD.
▶	COMBINATION VOICE/DATA OUTLET. OUTLET BOX WITH 1" C STUBBED ABOVE ACCESSIBLE CEILING SPACE AND PULL CORD.
☑	COMBINATION VOICE/DATA FLOOR OUTLET. OUTLET BOX WITH 1" C STUBBED ABOVE ACCESSIBLE CEILING SPACE AND PULL CORD.
→	4'-0" HIGH x 3/4" THICK FIRE-RETARDANT PLYWOOD BACKBOARD. SEE PLANS FOR LENGTH.
2 ②	WIRELESS ACCESS POINT OUTLET CEILING MOUNTED. OUTLET BOX WITH 1" C STUBBED ABOVE ACCESSIBLE CEILING SPACE AND PULL CORD. NUMBER INDICATES QUANTITY OF DATA JACKS. ABSENCE OF A NUMBER INDICATES ONE DATA JACK.
■	CABLE TRAY

	CIRCUIT BREAKER, TRIP RATING AS INDICATED, 3 POLE OR AS INDICATED
	DISCONNECT SWITCH OR LOAD INTERRUPTER SWITCH, CURRENT RATING AS INDICATED, 3 POLE OR AS INDICATED
	SWITCH WITH GROUND FAULT INTERRUPTER
	FUSE, CURRENT RATING AND TYPE WHEN INDICATED
	TRANSFORMER, DESCRIPTION AS NOTED OR PER SCHEDULE
	CURRENT TRANSFORMER
	POTENTIAL TRANSFORMER
	PHASE SELECTOR SWITCH
	AMMETER
	VOLTMETER
	WATT-HOUR METER
	SURGE PROTECTIVE DEVICE
	AUTOMATIC TRANSFER SWITCH
	GENERATOR

\$ ₁	SWITCH, SINGLE POLE, 20A
\$ ₂	SWITCH, DOUBLE POLE, 20A SWITCH
\$ ₃	3-WAY, 20A SWITCH
\$ ₄	4-WAY, 20A SWITCH
\$ _K	KEY OPERATED
\$ _P	SINGLE POLE SWITCH, WITH PILOT LIGHT
\$ _M	SINGLE POLE MANUAL MOTOR STARTING SWITCH, WITH THERMAL OVERLOAD ELEMENT AND PROVISIONS FOR LOCKING OPEN
\$ _D	SWITCH, DIMMING (COORDINATE WITH FIXTURE MANUFACTURER)
\$ _X	SWITCH, MULLION SWITCH
\$ _{LV}	LOW VOLTAGE WITH MOMENTARY CONTACTS SWITCH
\$ _O	OCCUPANCY SENSOR, WALL MOUNTED, DUAL TECHNOLOGY
\$ _O	OCCUPANCY SENSOR, CEILING MOUNTED, DUAL TECHNOLOGY
\$ _{PC}	PHOTOCELL
	MULTIPLE DEVICES LOCATED SIDE BY SIDE (OR ABOVE AND BELOW, IF DIFFERENT ELEVATIONS ARE SHOWN) AT THE LOCATION INDICATED)

Sheet Number

E-001